



RF Systems, Inc.
 26H World's Fair Drive
 Somerset, NJ 08873
 (732) 563-1144
 www.dsirf.com

Model UCS-1000 Universal Camera Controller

Supervisor Mode

Permits access to the camera menu tree to adjust all camera parameters

Menu: Toggles the onscreen menu

Item Up: Steps Upward thru the onscreen menu

Item Down: Steps Downward thru the onscreen menu

Left: Steps Left thru the selected parameter menu

Right: Steps Right thru the selected parameter menu

Switch Illuminates only in Supervisor Mode

Preset Functions

Playback Procedure:

- 1) Press knob to activate Playback Presets
- 2) Rotate knob to the desired preset
- 3) Press knob to execute playback preset

Record Procedure:

- 1) Press Record button to activate recording Presets
- 2) The record switch will illuminate
 (Note that there is a built in delay to prevent accidental activation)
- 3) Rotate knob to the desired preset
- 4) Press Record button to store preset

Zoom Control

Toggle action zooms camera Wide or Tele

Iris Control

Adjusts the Iris when in Manual mode

To select Manual mode depress the On/Off switch until the switch is illuminated.
 (Note that there is a built in delay to prevent accidental activation)

Adjust the Iris knob for the desired iris opening

Operates with Supervisor mode on or off

Camera Functions

Executes Camera functions
 All switches are momentary and operate with Supervisor mode on or off

System Controls

Executes system functions
 These are toggle functions. Press once for on and again for off
 The Wiper switch, when activated, also automatically washes the view window for 1.5 seconds
 All switches are momentary and operate with Supervisor mode on or off

Supervisor eKey

Application of the Supervisor iButton key to the reader will activate the Supervisor Menu
 Use the Selector knob to select the Supervisor Mode
 Depress the Selector knob to select your choice
 The Menu switch illuminates to verify the Supervisor Mode is on

Selector

Selects the desired Site Control channel and Supervisor mode selections

Site or Supervisor Mode Selection Procedure:

- 1) Press knob to bring up menu on the display
- 2) Rotate knob to desired choice
- 3) Press knob to select choice

Display

Displays all system data

